A Tallysman Accutenna[™] TW3752 High Gain / High Rejection GPS + GLONASS + Galileo + BeiDou Timing Antenna

The TW3752 is a high-gain GPS + GLONASS + Galileo + BeiDou antenna specifically designed for timing applications in high density cell / telecommunications tower applications where high levels of near-out-of-band interfering signals can be expected.

The TW3752 covers the GPS L1, GLONASS G1, Galileo E1, BeiDou B1, and SBAS (WAAS, EGNOS & MSAS) frequency band and employs Tallysman's unique $Accutenna^{\text{TM}}$ technology to provide excellent cross polarization rejection and greatly enhanced multipath rejection.

The TW3752 features triple SAW filters including a tight, low loss pre-filter to protect against saturation by high level sub-harmonic and L-Band signals. This antenna also features a 50dB LNA gain to handle the long cable runs sometimes associated with telecommunications towers.

The TW3752 housing has a permanent mount, IP67 compliant metal base, and an extended temperature range plastic radome, and is specifically designed to withstand the most challenging environmental conditions.

Two options for pole mounting are available an L-bracket (P/N#23-0040-0) or a pipe mount (P/N#23-0065-0).

Applications

Tallysman

- Timing systems
- Long cable runs

Features

- Dual Feed Patch Antenna
- Low Loss SAW Pre-Filter
- Great axial ratio: 1 dB typ.
- Low noise LNA: < 2.5 dB typ.
- Triple High rejection SAW filter
- High gain LNA: 50 dB typ.
- Low current: 30 mA typ.
- Wide voltage input range: 2.7 to 26 VDC
- IP67 weather proof housing

Benefits

- Great out of band rejection
- Excellent multipath rejection
- Excellent circular polarisation

66.5Ø

47 5

4 3

4 MAX

R8

R80 ·

R20

28.7

14.2

- Excellent signal to noise ratio
- Increased system accuracy
- Ideal for harsh environments
- RoHS compliant

TW3752 High Gain / High Rejection GPS + GLONASS + Galileo + BeiDou Timing Antenna

Specifications

Tallysman

Antenna

Architecture 1 dB Bandwidth Antenna Gain (with 100mm ground plane) Axial Ratio (over full bandwidth)

Electrical

Filtered LNA Frequency Bandwidth Polarization LNA Gain Gain flatness Out-of-Band Rejection <1525 MHz >1650 MHz

VSWR (at LNA output) Noise Figure Supply Voltage Range (over coaxial cable) Supply Current ESD Circuit Protection

Mechanicals & Environmental

Mechanical Size Operating Temp. Range Enclosure Weight Attachment Method Environmental Shock Vibration Dual, Quadrature Feeds 47 MHz 4.5 dBic @ 90° <1 dB @zenith typ., 3 dB max.

1559 to 1606 MHz RHCP 50 dB min., across full bandwidth +/- 2dB, 1559 to 1606 MHz >60 dB <1.5:1 2.5 dB typ 2.7 to 26 VDC nominal 30 mA typ.,35mA max 15 KV air discharge

66.5 mm dia. x 21 mm H -40 to +85 °C Radome: EXL9330, Base: Zamak White Metal (M18x1thread) 150 g Permanent ¾" (19mm) through hole mount IP67 and RoHS compliant Vertical axis: 50 G, other axes: 30 G 3 axis, sweep = 15 min, 10 to 200 Hz sweep: 3 G

Ordering Information

TW3752 – High Gain / High Rejection 4 Constellation Timing Antenna 33-3752-xx-yy-zzzz

Where xx = connector type, yy = shape and colour of radome, and zzzz = cable length in mm (where applicable)

Please refer to the Ordering Guide (<u>http://www.tallysman.com/wp-content/uploads/Current-Ordering-Guide.pdf</u>)) for the current and complete list of available radomes and connectors.

Tallysman Wireless Inc

106 Schneider Road, Unit 3Ottawa ON K2K 1Y2 CanadaTel 613 591 3131Sales@tallysman.com

The information provided herein is intended as a guide only and is subject to change without notice. This document is not to be regarded as a guarantee of performance. Tallysman Wireless Inc. hereby disclaims any or all warranties and liabilities of any kind. © 2015 Tallysman Wireless Inc. All rights reserved. Rev 1.0