Trimble AV16 Antenna HELIX BASED DUAL-FREQUENCY ANTENNA FOR UAV APPLICATIONS

+ + +

The Trimble AV16 antenna is a helix based dual-frequency L-band antenna. This antenna is ideal for UAV applications due to its lightweight, small form factor and low power consumption design.

COMPREHENSIVE GNSS SUPPORT

The Trimble AV16 offers support for GPS L1/L2, GLONASS L1/L2, Galileo E1 and BeiDou B1 as well as Trimble RTX and OmniSTAR correction services via L-Band.

DESIGNED FOR ACCURACY

Trimble AV16 features a precision tuned, helix element. It offers excellent axial ratio and does not require a ground plane for optimal performance. In addition, the antenna has an integrated low-loss pre-filter to increase the antenna's immunity to high amplitude interferencing signals from LTE and other cellular signals. The antenna also has an integrated SMA connector for easy screw-on mounting as well as an O-ring to comply with IP67 standards.

Additional key features of the AV16 include:

- ▶ Very low noise preamp: 1.7dB
- Axial ratio: <0.5dB max</p>
- LNA Gain: 35dB typ
- ► Low current: 21mA typ
- ESD circuit protection: 15 KV
- Invariant performance from: +2.2 to 16VDC

Key Benefits

+ + + + + + + + + + +

- Lightweight at 37g
- Small footprint
- Great multipath rejection
- Increased system accuracy
- Excellent signal to noise ratio
- ▶ IP67, REACH and RoHS compliant

Trimble





TECHNICAL SPECIFICATIONS

@ Vcc = 3V and 25 °C ambient temperature Antenna Element Architecture

| Element Architecture | Dual-Frequency |
|----------------------|------------------------|
| | RHCP Quadrifilar Helix |
| Phase Center | L1/E1/B1: 0.032m |
| | L2/G2: 0.037m |

| | | | L2/G2: 0.03/m |
|--|-----|-------------------------------------|-------------------------------|
| GNSS | | Gain
(dBic typ at Zenith) | Axial Ratio
(dB at Zenith) |
| GPS / QZSS | L1 | 3.3 | ≤ 0.5 max |
| | L2 | 1.8 | ≤ 0.5 max |
| | L5 | - | _ |
| GLONASS | L1 | 2.8 | ≤ 0.5 max |
| | L2 | 1.5 | ≤ 0.5 max |
| | L3 | - | _ |
| Galileo | E1 | 3.3 | ≤ 0.5 max |
| | E5a | - | _ |
| | E5b | - | _ |
| | E6 | _ | _ |
| BeiDou | B1 | 3.1 | ≤ 0.5 max |
| | B2 | - | _ |
| | B2a | - | _ |
| | B3 | - | _ |
| IRNSS / NavIC | L5 | - | - |
| QZSS | L6 | _ | _ |
| L-Band Services
(1525MHz - 1559MHz) | | 2.9 | ≤ 0.5 max |



Trimble AV16 Antenna

+ +

10000

+ + + + + + + +

1000041

ELECTRICAL SPECIFICATIONS

+

. .

| 1525MHz - 1606MHz |
|-----------------------|
| 1215MHz - 1254MHz |
| |
| 1.7dB typ |
| <1.5:1 typ |
| 1.8:1 max |
| +2.2 to 16VDC |
| 21mA typ at 25 °C |
| . 15 KV air discharge |
| pting L1 +/- 100MHz |
| and L2 +/- 100 MHz |
| |

Out-of-Band Rejection

| _ | | | |
|----------|-------|----------|-------|
| L1 | | L2 | |
| <1400MHz | >36dB | <1100MHz | >35dB |
| <1450MHz | >32dB | <1190MHz | >47dB |
| >1700MHz | >45dB | >1350MHz | >48dB |

PHYSICAL & ENVIRONMENTAL SPECIFICATIONS

| Mechanical Size | 62.4 mm (H) x 44.2 mm (D) |
|----------------------------|---------------------------------------|
| Weight | |
| Connector | SMA Male |
| Operating Temperature Rang | ge40 °C to +85 °C |
| Enclosure | Radome: EXL9330, Base: EXL9330 |
| Environmental | IP67, RoHS and REACH compliant |
| Shock | Vertical axis: 50 G, Other axes: 30 G |
| Vibration 3 axis, swee | ep = 15 min, 10 to 200Hz sweep: 3 G |
| | |

PART NUMBER

120982-16..... Trimble AV16 GNSS Antenna

Specifications subject to change without notice.

Trimble



TRIMBLE Integrated Technologies 510 DeGuigne Drive Sunnyvale, CA 94085

Sunnyvale, CA 94085 Americas & Asia-Pacific Europe/EMEA

Email: sales-intech@trimble.com

Contact your local Trimble Authorized Distribution Partner for more information

© 2020, Trimble Navigation Limited. All rights reserved. Trimble logo are trademarks of Trimble, registered in the United States and in other countries. All other trademarks are the property of their respective owners. (02/20)