HC976



HC976 Triple-Band Helical Antenna + L-Band

 Frequency
 GNSS/QZSS-L1/L2, QZSS-L6, GLONASS-G1/G2, Galileo-E1/E6, BeiDou-B1/B3

 Coverage:
 + L-Band correction services

Overview

The patented HC976 helical antenna is designed for precision positioning, covering the GPS/QZSS-L1/L2, QZSS-L6, GLONASS-G1/G2, Galileo-E1/E6, and BeiDou-B1/B3 frequency bands, including the satellite-based augmentation system (SBAS) available in the region of operation [WAAS (North America), EGNOS (Europe), MSAS (Japan), or GAGAN (India)], as well as L-Band correction services.

Weighing only 42 g, the light and compact HC976 features a precisiontuned helix element that provides excellent axial ratios and operates without the requirement of a ground plane, making it ideal for a wide variety of applications, including unmanned aerial vehicles (UAVs).

The HC976 features an industry-leading low current, low-noise amplifier (LNA) that includes an integrated low-loss pre-filter to prevent harmonic interference from high-amplitude signals, such as 700 MHz band LTE and other nearby in-Band cellular signals.

All Tallysman housed helical antenna elements are protected by a robust military-grade IP69K-compliant plastic enclosure. The enclosure's base provides two threaded inserts for secure attachment, as well as a rubber O-ring around the outer edge to seal the antenna base and its integrated male SMA connector.

Tallysman's helical family has passed a rigorous 30-hour vibration test procedure, consisting of five cycles of 2-hour tests per axis (x, y, z):

- Cycle 1: 1.05 Grms;
- Cycle 2: 1.20 Grms;
- Cycle 3: 1.35 Grms;
- Cycle 4: 3.67 Grms;
- Cycle 5: 3.67 Grms.

For mounting instructions, visit: https://www.tallysman.com/downloads/Helical_Mounting_Instruction.pdf

Applications

- Autonomous unmanned aerial vehicles (UAVs)
- Precision GNSS positioning
- Precision land survey positioning
- Mission-critical GNSS timing
- Network timing and synchronization
 Sea and land container tracking
- Fleet management and asset tracking
- Marine and avionics systems
- Law enforcement and public safety
- Features
- Very low noise preamp (1.8 dB typ.)
 Axial ratio (≤ 0.5 dB at zenith)
- Axial ratio (≤ 0.5 dB at zenith)
 LNA gain (28 dB typ. | 35 dB typ.)
- LNA gain (28 dB typ. | 35 dB typ.)
 Low current (15 mA typ. | 21 mA typ.)
- ESD circuit protection (15 kV)
- Invariant performance from 2.2 to 16 VDC
- IP69K, REACH, and RoHS compliant

Benefits

- Extremely light (42 g)
- Ideal for RTK and PPP surveying systems
- Excellent RH circular polarized signal
- reception
- Great multipath rejection
- Increased system accuracy
- Excellent signal-to-noise ratio
 Industrial temperature range
- Rugged design, ideal for harsh environments

About Tallysman: With global headquarters and manufacturing in Ottawa, Canada, Tallysman is a leading manufacturer of high-precision antennas and components for Global Navigation Satellite System (GNSS) applications. Tallysman's mission is to support the needs of a new generation of positioning systems by delivering unprecedented antenna precision at competitive prices. Learn more at www.tallysman.com

Contact us: info@tallysman.com T: +1 613 591-3131



HC976 Triple-Band Helical Antenna + L-Band

Frequency Coverage:

Technology

GNSS/QZSS-L1/L2, QZSS-L6, GLONASS-G1/G2, Galileo-E1/E6, BeiDou-B1/B3 + L-Band correction services

Antenna

Triple-frequency, RHCP quadrifilar helix

			Gain	Axial Ratio	
			dBic typ. at Zenith	dB at Zenith	
GNSS					
		L1	2.5	≤ 0.5	
GPS / QZSS		L2	1.4	≤ 0.5	
		L5	-	-	
		G1	1.5	≤ 0.5	
GLONASS		G2	2.6	≤ 0.5	
		G3	-	-	
Galileo		E1	2.5	≤ 0.5	
		E5A	-	-	
Gameo		E5B	-	-	
		E6	1.6	≤ 0.5	
BeiDou		B1	2.5	≤ 0.5	
		B2	-	-	
Belbou		B2a	-	-	
		B3	2.3	≤ 0.5	
IRNSS / NavIC		L5	-	-	
QZSS		L6	1.6	≤ 0.5	
L-Band Services (1525 MHz - 1559 MHZ))	1.5	≤ 0.5	
Satellite Communications					
Iridium		-	-		
Globalstar		-	-		
Other					
Axial Ratio at 10°		-	Efficiency	-	
PC Variation	± 3.0 mm	(all freq.)	PCO		

Mechanicals

Mechanical Size	44.2 mm (dia.) x 62.4 mm (h.)
Weight	42 g
Radome	3x M2.5 screws
Mount	SMA (male)
Available Connectors	Radome and Base: EXL9330

Environmental

Operating Temperature	-40 °C to + 85 °C
Storage Temperature	-50 °C to + 95 °C
Vibration	MIL-STD-810E - Test method 514.5
Shock	MIL-STD-810E - Test method 514.5
Salt Fog	-
IP Rating	IP69K
Compliance	IPC-A-610, FCC, RED / CE Mark, RoHS, REACH

Warranty:

Parts and Labour 3-year standard warranty

Low Noise Amplifier (LNA) - Measured at 3V and 25°C

Frequency	Bandwith	Out of Band Rejection	
Lower Band	1217 - 1300 MH	z Pre-filter → LNA	
L-Band - Correction Services	1217 - 1300 MH	z	
Upper Band	1559 - 1606 MH:	> 32 dB @ < 1500 MHz > 30 dB @ > 1700 MHz	
Architecture	28 dB	typ. 35 dB typ.	
Gain		1.8 dB typ.	
Noise Figure	< 1.5:	< 1.5:1 typ. 1.8:1 max.	
VSWR	2.2 to	2.2 to 16 VDC	
Supply Voltage R	ange 15 mA	15 mA typ. (28 dB) 21 mA typ. (35 dB)	
Supply Current	15 kV	15 kV air discharge	
ESD Circuit Prote	ction 12 dB	12 dBm @ L1	
P 1dB Output	5 ns @	5 ns @ L1 5 ns @ L2	
Group Delay	5 ns @	5 ns @ L1 5 ns @ L2	

Mechanical Diagram



Ordering Information

Part Number

33-HC976-xx

where xx = gain (28 or 35 dB)

Please refer to our **Ordering Guide** to review available radomes and connectors at: https://www.tallysman.com/resource/tallysman-ordering-guide/

© 2022 Tallysman Inc. All rights reserved. Tallysman, the "When Precision Matters" tag line and the Tallysman logo are trademarks or registered trademarks of Tallysman Inc. and/or its affiliates in Canada and certain other countries. All other trademarks mentioned in this document are the property of their respective owners. The information presented is subject to change without notice. Tallysman assumes no responsibility for any errors or omissions in this document. Tallysman Wireless inc. hereby disclaims any or all warranties and liabilities of any kind.

www.tallysman.com

Revision: 20