TW5350/TW5351

Multi-Constellation Smart Antenna

Overview

The TW5350 is a multi-constellation GNSS Smart Antenna which provides **simultaneous** multi-constellation GNSS reception. It is designed for use in professional grade applications such as precision timing, network synchronization, low current applications, and tracking/positioning applications.

The TW5350 GNSS Smart Antenna uses the state-of-the-art multi-constellation GNSS receiver which provides 72 high sensitivity tracking channels which can be configured to acquire and track 3 concurrent GNSS constellations (GPS, Galileo, GLONASS and Beidou) plus SBAS (WAAS, EGNOS, MSAS and GAGAN) and QZSS augmentation signals simultaneously. Differential GPS corrections may also be supplied via RTCM formatted corrrections messages.

The TW5350 employs Tallysman's Accutenna™ dual feed antenna patch technology which greatly improves rejection of multi-path signal interference, across the whole GNSS band. The addition of pre- and post- filtering within the RF signal chain greatly improves immunity to jamming carriers typical within urban environments.

The TW5350 can be configured to output a variety of NMEA 0183 message lists with navigation update rates up to 5Hz. An RS232 interface is provided for data communication with input voltage options of 3.3V and 5-36V with over-voltage protection.

A configurable one pulse-per-second (1PPS) synchronized to UTC time is made available as a RS422 differential signal.

Tallymatics' Windows™ based Configurator enables simple configuration of parameters such as baud rates, output message rates, constellation, tracking parameters and 1PPS configuration and Standby mode parameters.

A non-magnetic version is available with Part Number TW5351.

t is designed for fon timing, network ng/positioning e-art multi-constellation

Accutenna[™] Technology
Pre- and Post- LNA filtering

- Superior multi-path signal rejection
- Low Current Standby Mode
- Industrial grade IP69K enclosure
- LSZH cable option for indoor application
- RoHS, REACH and RED Compliant.
- CE, UKCA, ISO:13766-1

Features

- Multi-Constellation Receiver/Antenna
- Concurrent tracking of 3 constellations
- 72 Channel simultaneous
- High performance tracking (-167 dBm)
- WAAS, EGNOS, MSAS & GAGAN + QZSS
- DGPS corrections using RTCM input
- Navigation rates 1 to 5 Hz
- 1 PPS RS422 outputs



When precision matters.®





tollation Dessive

TW5350/TW5351 Multi-Constellation Smart Antenna

Specifications

Antenna	
SBAS L1 C/A	
Interface	
Pwr, Gnd Tx, RX	RS232 RS422 (30kV protection)
Mechanical	
Weight Mounting Method Cable Length	0
Electrical	
-	5-36 VDC (Overvoltage Protection) <500 mW nominal Operating
Environmental	
	40°C to +85°C

nsitivity king & Nav 4Bm 1 starts-148 dBm starts-157 dBm quisition Aided 3 sec quisition1 sec uracy ding Accuracy0.3 deg erational Limits ude......50,000 m rial Protocol out.....NMEA 0183 tRTCM d Rate..... Configurable up to 230400 bps ate Rate.....Configurable up to 5Hz ne Pulse CycleConfigurable

Ordering Information:

33-5350-7-yy-zz-PC0 Standard GNSS Smart Antenna, 33-5351-7-yy-zz-PC0 Non-magnetic GNSS Smart Antenna

-PC0 (Default factory configuration) Please inquire regarding custom factory configuration options.

DB9 Test adaptor 27-0045-1

Please refer to the Ordering Guide for the current and complete list of available product options.



When precision matters.®

About Tallysman: With global headquarters and manufacturing in Ottawa, Canada, Tallysman is a leading manufacturer of high-precision antennas and components for Global Navigation Satellite System (GNSS) applications. Tallysman's mission is to support the needs of a new generation of positioning systems by delivering unprecedented antenna precision at competitive prices. Learn more at **www.tallysman.com**

© 2023 Tallysman Inc. All rights reserved. Tallysman, the "When Precision Matters" tag line and the Tallysman logo are trademarks or registered trademarks of Tallysman Inc. and/or its affiliates in Canada and certain other countries. All other trademarks mentioned in this document are the property of their respective owners. The information presented is subject to change without notice. Tallysman susues no responsibility or any errors or omissions in this document. Tallysman Wireless Inc. hereby disclaims any or all warranties and liabilities of any kind.

Tallysman - TW5350 TW5351 - Datasheet EN

Contact us:

info@tallysman.com T: +1 613 591-3131